

HOJA DE DATOS TÉCNICOS



FECHA:

01-01-2016

DENOMINACIÓN:

PINZA AMPERIMETRICA DIGITAL AC

ARTÍCULO:

KPS-PA05



This meter is one of a series portable 3 1/2 digital clamp meter for measuring DC and AC Voltage, AC current, resistance, continuity test and insulation test. Some models also provide frequency or temperature test. Full overload protection. Low battery indication and over-range indication are providing. Following table shows function of the series of clamp meter.

- Display: 2000 counts
- Jaw Opening: $\Phi 50\text{mm}/2.0''$
- Diode: 2.7V
- Continuity Buzzer: $<100\Omega$
- Data Hold
- Low Battery Display

Specification	Range	Accuracy
DC Voltage	2V/20V/200V	+-(0.5%+3)
	1000V	+-(0.8%+3)
AC Voltage	200V	+-(1.0%+5)
	750V	+-(1.2%+5)
AC Current	200A	+-(2.5%+5)
	1000A	+-(3.0%+10)
Resistance	200 Ω	+-(1.0%+5)
	2K Ω /20K Ω /200K Ω /2M Ω	+-(1.0%+8)
Frequency	2kHz	+-(2.0%+5)

ARTICULO: 602150022